

**Equipment Configuration Checklist Integrated with VITAL (TSys) (credit/debit)**

	<u>Paper Check w/o Chk Rdr</u>	<u>Paper Check w/ Chk Rdr</u>	<u>Check Conversion w/ Imager (quar only)</u>	<u>Check Conversion w/ Chk Rdr (verify only)</u>	<u>Gift Card</u>	<u>Loyalty</u>	<u>Comments:</u>
<b>Lipman:</b> Nurit 2085 / 2085+ / 3000 / 3020	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f	Magtek Mini MICR	Yes	Yes	NOS 7 upgrade, unless paper check. 3000 model can not upgrade to NOS 7; only paper check or stand alone. Credit Card support downgraded to Class B. Loses ability to auto settle. Franking option available with the RDM EC6004i/EC6005i/EC6014f.
<b>Lipman:</b> Nurit 3010 / 8000	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f	Magtek Mini MICR	Yes	Yes	Same as above... Only models 10 and 12 of the 3010 can be upgraded to NOS 7. Nurit 8000 does not have ability to connect a check reader/imager, unless connected to base. Must have a physical analog telephone connection. Franking option available with the RDM EC6004i/EC6005i/EC6014f.
<b>Lipman:</b> 8320	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f	Magtek Mini MICR	Yes	Yes	Credit Card support downgraded to Class B. Loses ability to auto settle. Franking option available with the RDM EC6004i/EC6005i/EC6014f. 8320 Model 14A is a proprietary terminal, SPS cannot load it, the acquirer must add SPS.
<b>Thales:</b> Talento	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f	Magtek Mini MICR	Yes	No	Franking option NOT available with the EC6004i/EC6005i/EC6014f.
<b>Verifone:</b> Omni 3200	Yes	Magtek Mini MICR	No	No	No	No	
<b>Verifone:</b> Omni 3730 (Vx510) / 3740 / 3750	Yes	Yes Magtek Mini MICR	Yes EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f CR1000 Magtek MICR Imager	Yes Magtek Mini MICR	Yes Yes	Yes Yes	3730 model does not support dual comm (IP) & can only accommodate 2 applications. If integrating credit, debit, check and gift/loyalty, terminal must be 4 MEG (minimum). IP or Dual Comm needed if loading an IP Application. Franking option available with the RDM EC6004i/EC6005i/EC6014f.
<b>Verifone:</b> Vx570 / Vx610 / Vx510 (Omni 3730)	Yes	Yes Magtek Mini MICR	Yes EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f CR1000 Magtek MICR Imager	Yes Magtek Mini MICR	Yes Yes	Yes Yes	Vx510 model does not support dual comm (IP) & can only accommodate 2 applications. If integrating credit, debit, check and gift/loyalty, terminal must be 4 MEG (minimum). IP or Dual Comm needed if loading an IP Application. Franking option available with the RDM EC6004i/EC6005i/EC6014f. Vx610 must have physical analog phone or IP connection.
<b>Verifone:</b> Tranz 330 / 380 / 460	Yes	Magtek Mini MICR	No	No	No	No	See Stand Alone SPS checklist for conversion and gift possibilities.
<b>Verifone:</b> Tranz 380x2	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f	Magtek Mini MICR	Yes	No	Franking option available with the RDM EC6004i/EC6005i/EC6014f.
<b>TechTrex:</b> PrimeTrex / PrimeTrex IP / "PAI-Trex"	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f Magtek MICR Image	Magtek Mini MICR	Yes	Yes	ConverTrex needed if using IP with PrimeTrex. Franking option available with the RDM EC6004i/EC6005i/EC6014f.
<b>Ingenico:</b> Elite 510 / 512 / 710 / 712	Yes	encheck 2500	encheck 2600	encheck 2500	Yes	No	
<b>TechTrex:</b> PrimeTrex	Yes	Yes Magtek Mini MICR	Yes EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f CR1000 Magtek MICR Imager	Yes Magtek Mini MICR	Yes Yes	Yes Yes	Franking option available with the RDM EC6004i/EC6005i/EC6014f. ConverTrex needed if using IP with a PrimeTrex.
<b>TechTrex:</b> PrimeTrex IP ("PAI-Trex")	Yes	Yes Magtek Mini MICR	Yes EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f CR1000 Magtek MICR Imager	Yes Magtek Mini MICR	Yes Yes	Yes Yes	Franking option available with the RDM EC6004i/EC6005i/EC6014f. PrimeTrex IP and PAI Trex do not need ConverTrex for IP
<b>Hypercom:</b> T4100	Yes	Yes Magtek Mini MICR	Yes EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f	Yes Magtek Mini MICR	Yes Yes	Yes Yes	Franking option available with the RDM EC6004i/EC6005i/EC6014f.
<b>Hypercom:</b> T7p / T77 / Plus	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f Magtek MICR Image (see comments)	Magtek Mini MICR	Yes	No	Requires SPOS09 software and acquirer willing to add SPS. SPS can build a dnl file if provided VAR for other services. Franking option available with the RDM EC6004i/EC6005i/EC6014f. Must be 512K or higher. If using the Magtek MICR Imager it must be ordered with 9600 bps.
<b>Hypercom:</b> ICE 5500	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005i EC6004i/EC6005f EC6014i/EC6014f Magtek MICR Image (see comments)	Magtek Mini MICR	Yes	No	Requires SPOS09 software and acquirer willing to add SPS. SPS can build a dnl file if provided VAR for other services. Franking option available with the RDM EC6004i/EC6005i/EC6014f. Must be 512K or higher. If using the Magtek MICR Imager it must be ordered with 9600 bps.
<b>Hypercom:</b> ICE 5700	No	Yes (integrated)	No	Yes (integrated)	Yes	No	Requires SPOS09 software and acquirer willing to add SPS. SPS can build a dnl file if provided VAR for other services. Must be 512K or higher.

(last updated 4/20/08)