

Equipment Configuration Checklist Integrated with Concord EFS (credit/debit)

	<u>Paper Check w/o Chk Rdr</u>	<u>Paper Check w/ Chk Rdr</u>	<u>Check Conversion w/ Imager (quar only)</u>	<u>Check Conversion w/ Chk Rdr (verify only)</u>	<u>Gift Card</u>	<u>Loyalty</u>	<u>Comments:</u>
<u>Lipman</u> : Nurit 2085 / 2085+ / 3000 / 3020	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005f EC6004f/EC6005f EC6014i/EC6014f	Magtek Mini MICR	Yes	Yes	NOS 7 upgrade, unless paper check. 3000 model can not upgrade to NOS 7; only paper check or stand alone. Credit Card support downgraded to Class B. Loses ability to auto settle. Franking option available with the RDM EC6004f/EC6005f/EC6014f.
<u>Lipman</u> : Nurit 3010 / 8000	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005f EC6004f/EC6005f EC6014i/EC6014f	Magtek Mini MICR	Yes	Yes	Same as above... Only models 10 and 12 of the 3010 can be upgraded to NOS 7. CDPD / Motient only. Nurit 8000 does not have ability to connect a check reader/imager. Check conversion not possible without dial out. Franking option available with the RDM EC6004f/EC6005f/EC6014f.
<u>Lipman</u> : 8320	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005f EC6004f/EC6005f EC6014i/EC6014f	Magtek Mini MICR	Yes	Yes	Credit Card support downgraded to Class B. Loses ability to auto settle. Franking option available with the RDM EC6004f/EC6005f/EC6014f. 8320 Model 14A is a proprietary terminal, SPS cannot load it, the acquirer must add SPS. TCP/IP compatible
<u>Verifone</u> : Omni 3200	Yes	Magtek Mini MICR	No	No	No	No	
<u>Verifone</u> : Omni 3730 (Vx510) Omni 3740 Omni 3750 Vx570	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005f EC6004f/EC6005f EC6014i/EC6014f CR1000 Magtek MICR Imager	Magtek Mini MICR	Yes	Yes	3730 (Vx510) model does not support dual comm (IP) & can only accommodate 2 applications. If integrating credit, debit, check and gift/loyalty, terminal must be 4 MEG. Dualcomm needed if loading an IP Application. Franking option available with the RDM EC6004f/EC6005f/EC6014f.
<u>Verifone</u> : Tranz 330 / 380 / 460	Yes	Magtek Mini MICR	No	No	No	No	See Stand Alone SPS checklist for conversion and gift possibilities.
<u>Verifone</u> : Tranz 380x2	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005f EC6004f/EC6005f EC6014i/EC6014f	Magtek Mini MICR	Yes	pending	Franking option available with the RDM EC6004f/EC6005f/EC6014f.
<u>Ingenico</u> : Elite 510 / 512 / 710 / 712	See Comments	See Comments encheck 2500	See Comments encheck 2600	See Comments encheck 2500	See Comments	No	Concord must provide the terminal password in order to download any SPS app.
<u>Hypercom</u> : T7p / T77 / Plus	See Comments	See Comments Magtek Mini MICR	See Comments EC5003i / EC5004i EC6004i / EC6005f EC6004f/EC6005f EC6014i/EC6014f Magtek MICR Imager (see comments)	See Comments Magtek Mini MICR	See Comments	pending	Requires SPOS09 software and acquirer willing to add SPS. Franking option available with the RDM EC6004f/EC6005f/EC6014f. Must be 512K or higher. If using the Magtek MICR Imager it must be ordered with 9600 bps.
<u>Hypercom</u> : ICE 5500	See Comments	See Comments Magtek Mini MICR	See Comments EC5003i / EC5004i EC6004i / EC6005f EC6004f/EC6005f EC6014i/EC6014f Magtek MICR Imager (see comments)	See Comments Magtek Mini MICR	See Comments	pending	Requires SPOS09 software and acquirer willing to add SPS. Franking option available with the RDM EC6004f/EC6005f/EC6014f. Must be 512K or higher. If using the Magtek MICR Imager it must be ordered with 9600 bps.
<u>Hypercom</u> : ICE 5700	No	See Comments (integrated)	No	See Comments (integrated)	See Comments	pending	Requires SPOS09 software and acquirer willing to add SPS. Must be 512K or higher.
<u>TechTrex</u> : PrimeTrex	No	No	No	No	Yes	Yes	TCP/IP compatible with use of <i>PrimeTrex ConverTrex</i> IP. Requires one "free" chip for download.

(last updated 2/19/07)